

## Honeywell Sensing and Control

Search



### narrow your search

#### Products

- Controls Monitoring and Lighting (286)
- Machine Safety (1727)
- Sensors (6158)
- Switches (9781)
- Wireless (45)

#### Technology

- Control and Instrumentation (890)
- Electromechanical (9303)
- Magnetic (538)
- Platinum thin film (56)
- Thick Film (1372)
- More...

### new products

#### New Wireless Products

Go farther. Work smarter. Explore new possibilities. Just by cutting the cord and making the switch.



Wireless Web Site  
WGLA and WPMM  
XYR6000™

[find out more](#)

### white papers

- Wireless Switches Offer Unlimited Benefit
- Basic Switches Are Not Created Equal
- Applying Precision Switches
- Sensors for Medical Devices
- New Ways to Measure Torque
- Choosing Safety Switches
- Specifying Hour Meters

### Need help?

[Click here to contact us](#)

### SA1CB1A103

(Home : Products : Sensors » Rotary Position Sensors » Conductive Plastic Potentiometers » SensorCube )



*Actual product appearance may vary.*

SensorCube Precision Potentiometer, Conductive Plastic Element, PC Terminals, 1 W Power Rating, 10 kOhm Resistance Value

[Sales & Service](#)

[Distributor Inventory](#)

[Overview](#) [Specs](#) [Documentation](#) [Application Notes](#)

#### Product Specifications

Potentiometer Type	Precision
Element Type	Conductive Plastic
Terminal	PC
Power Rating	1 W
Resistance Value	10 kOhm
Resistance Tolerance	± 10 %
Linearity	± 2 %
Bushing Thread	9,53 mm [0.375 in] x 32 NEF-2A
Bushing Length	9,53 mm [0.375 in]
Bushing Type	Standard
Shaft Diameter	6,35 mm [0.25 in]
Shaft Length	22,23 mm [0.875 in]
Shaft Ending	Flatted
Body	18,92 mm [0.745 in] diameter, ± 11,43 mm [0.450]
Electrical Taper	Linear
Operating Temperature	-65 °C to 125 °C [-85 °F to 257 °F]
Working Voltage (Max.)	750 V
Rotational Life	10 million cycles
Mechanical Rotation	310°
Availability	Global
Series Name	SensorCube
UNSPSC Code	4111363380
UNSPSC Commodity	4111363300 Potentiometers

### contacts

Customer Service  
Technical Support  
Global Sales & Service  
View Site Demo  
Site Comments?

### meet dr. larry

**VIDEO** - Dr. Larry Goldstein explains our newest and best technologies.

Meet Dr. Larry



### my links

[Login to iCOM](#)  
[Login to Rep/AD Portal](#)  
[Login to Digital University](#)

### News Center

HONEYWELL INTRODUCES TRUSTABILITY® NSC SERIES, UNCOMPENSATED / UNAMPLIFIED BOARD MOUNT PRESSURE SENSORS

HONEYWELL EXPANDS ITS LIMITLESS™ PLATFORM WITH THE LAUNCH OF ITS GLOBALLY AVAILABLE INDUSTRIAL WIRELESS RECEIVER

HONEYWELL EXTENDS ITS TRUSTABILITY® PRESSURE SENSOR PRODUCT LINE WITH A SINGLE SIDE LIQUID MEDIA OPTION

**MICRO SWITCH**  
Anniversary site